



B01520-01

Remote Control Panel with graphics LC module and RS485 interface

- English version
- Incl. graphics LCD module to display alarm, fault and disabled messages; incl. buzzer
- Incl. push buttons for message scrolling, switching off the buzzer and to choose the kind of displayed messages
- Incl. buttons for Reset FCP and Reset external sounders (protected by key switch)
- English texts on front fascia and LCD
- Can be connected directly to the Fire Control Panel interface (RS-485)
- Up to 63 LCD Repeater Panels connectable to one Fire Control Panel
- No network software required
- Incl. steel housing for surface mounting
- No configuration necessary because data is transmitted from the FCP
- Several LEDs for "In Operation", "Alarm", "Fault" and "Disabling"

Technical specifications

Operating voltage	24 V DC
Current consumption	35 mA
Interface	RS-485
Max. cable length to CIE	max. 1.200m
Housing	Steel housing, RAL 7035
Weight	1,0 kg
Dimensions (WxHxD)	240 x 180 x 28 mm