



## Order No | B01100-00

Product Group 1000

### Loop extension module

This loop module provides one additional loop for the "Solution F2" panel and it supports the Hochiki ESP detectors as well as Apollo XP95/Discovery detectors. 127 detectors, beacons and modules can be connected (Apollo 126). In case of using Hochiki's ESP protocol further 127 base sounders can be addressed in the upper address range.

#### TECHNICAL SPECIFICATIONS :

Quiescent current	9 mA
Loop current	max. 450 mA
Loop cable length	max. 3.500m (cableJY-(ST)Y-2x2x0,8
Weight	150 g
Dimensions (WxHxD)	120 x 60 x 20 mm

#### CERTIFICATIONS :

VdS No. : G 208 145